

C 电容	量程:2nF,20nF,200nF,2 μ F,20 μ F,200 μ F
	分辨率:1pF,10pF,100pF,1nF,10nF,100nF
	精度: $\pm(3\%rdg+3dgt)$
L 电感	量程:2mH,20mH,200mH,2H,20HF
	分辨率:1 μ H,10 μ H,100 μ H,1mH,10mH
	精度: $\pm(3\%rdg+3dgt)/2mH$
R 电阻	量程:200 Ω ,2k Ω ,20k Ω ,200k Ω ,2M Ω ,20M Ω
	分辨率:0.1 Ω ,1 Ω ,10 Ω ,100 Ω ,1k Ω ,10k Ω
	精度: $\pm(2\%rdg+3dgt)$